

Shine Bar 18Q

18pcs RGBWAUV 6in1



User Manual

Please read over this manual before operating this light

KEY AND DISPLAY FUNCTIONS

1. Key instruction



MENU: Table1 function loops add;

UP: function value add;

DOWN: function value decrease;

ENTER: save the setting;

2. Display instruction

No.	Show	Function
1	CH8/11/41/113	4 DMX channel model selection
2	D001	DMX address 001-512
3	R255	Red color brightness adjust 0-255
4	G255	Green color brightness adjust 0-255
5	B255	Blue color brightness adjust 0-255
6	H255	White color brightness adjust 0-255
7	P255	Amber color brightness adjust 0-255
8	U255	UV color brightness adjust 0-255
9	Pr01	Built-in programs Pr01-Pr30
10	SP01	Programs working speed SP01-SP16
11	AUTO	Testing mode,Auto/Sound mode
12	DISP	Display reverse setting

DMX512 Configuration

8/11 Channels Mode:

No.	CH8	CH11	Function	Specification
CH1	*	*	Main dimmer	RGBWAUV linear dimmer 0-255, from dark to bright
CH2	*	*	Strobe	Strobe 0-255 from slow to fast
CH3	*	*	Red dimmer	Red color linear dimmer 0-255, from dark to bright
CH4	*	*	Green dimmer	Green color linear dimmer 0-255, from dark to bright
CH5	*	*	Blue dimmer	Blue color linear dimmer 0-255, from dark to bright
CH6	*	*	White dimmer	White color linear dimmer 0-255, from dark to bright
CH7	*	*	Amber dimmer	Amber color linear dimmer 0-255, from dark to bright
CH8	*	*	UV dimmer	UV color linear dimmer 0-255, from dark to bright
CH9		*	Color mixing	Different kinds color effect combination
CH10		*	Built-in program	0-10: CH1-CH9 active 11-250: Built-in programs 251-255: Sound control

CH11		*	Program speed	0-255, from fast to slow
------	--	---	---------------	--------------------------

41 Channels Mode:

No.	Function	Specification
CH1	Main dimmer	RGBWAUV linear dimmer 0-255, from dark to bright
CH2	Strobe	Strobe 0-255 from slow to fast
CH3	G1 Red dimmer	Group1 Red color linear dimmer 0-255, from dark to bright
CH4	G1 Green dimmer	Group1 Green color linear dimmer 0-255, from dark to bright
CH5	G1 Blue dimmer	Group1 Blue color linear dimmer 0-255, from dark to bright
CH6	G1 White dimmer	Group1 White color linear dimmer 0-255, from dark to bright
CH7	G1 Amber dimmer	Group1 Amber color linear dimmer 0-255, from dark to bright
CH8	G1 UV dimmer	Group1 UV color linear dimmer 0-255, from dark to bright
.....
CH33	G6 Red dimmer	Group6 Red color linear dimmer 0-255, from dark to bright
CH34	G6 Green dimmer	Group6 Green color linear dimmer 0-255, from dark to bright
CH35	G6 Blue dimmer	Group6 Blue color linear dimmer 0-255, from dark to bright
CH36	G6 White dimmer	Group6 White color linear dimmer 0-255, from dark to bright
CH37	G6 Amber dimmer	Group6 Amber color linear dimmer 0-255, from dark to bright
CH38	G6 UV dimmer	Group6 UV color linear dimmer 0-255, from dark to bright
CH39	Color mixing	Different kinds color effect combination
CH40	Built-in program	0-10: CH1-CH39 active 11-250: Built-in programs 251-255: Sound control
CH41	Program speed	0-255, from fast to slow

113 Channels Mode:

No.	Function	Specification
CH1	Main dimmer	RGBWAUV linear dimmer 0-255, from dark to bright
CH2	Strobe	Strobe 0-255 from slow to fast
CH3	LED1 Red dimmer	LED1 Red color linear dimmer 0-255, from dark to bright
CH4	LED1 Green dimmer	LED1 Green color linear dimmer 0-255, from dark to bright
CH5	LED1 Blue dimmer	LED1 Blue color linear dimmer 0-255, from dark to bright
CH6	LED1 White dimmer	LED1 White color linear dimmer 0-255, from dark to bright
CH7	LED1 Amber dimmer	LED1 Amber color linear dimmer 0-255, from dark to bright
CH8	LED1 UV dimmer	LED1 UV color linear dimmer 0-255, from dark to bright
.....
CH105	LED18 Red dimmer	LED18 Red color linear dimmer 0-255, from dark to bright
CH106	LED18 Green dimmer	LED18 Green color linear dimmer 0-255, from dark to bright
CH107	LED18 Blue dimmer	LED18 Blue color linear dimmer 0-255, from dark to bright
CH108	LED18 White dimmer	LED18 White color linear dimmer 0-255, from dark to bright
CH109	LED18 Amber dimmer	LED18 Amber color linear dimmer 0-255, from dark to bright
CH110	LED18 UV dimmer	LED18 UV color linear dimmer 0-255, from dark to bright
CH111	Color mixing	Different kinds color effect combination
CH112	Built-in program	0-10: CH1-CH111 active 11-250: Built-in programs 251-255: Sound control
CH113	Program speed	0-255, from fast to slow

Specification:

Voltage: AC 90-240v, 50-60Hz

Power consumption: 250W

LED: 18pcs*15W RGBWAUV 6in1 LEDs

Each LED Individually Controlled

Control Mode: DMX512, master slave,Auto, Sound control

Channel: 8/11/41/113CH

Lens Angle: 40°

Function Effect:Dimmer,stroke,Eotic,Gradual Change

Cooling Mode:Intelligent Cooling System

Display: digital screen

IP rate: IP65

Over-temperature Protection

Dimensions: 106*120*16cm

Weight: 8kg